



US008830105B2

(12) **United States Patent**
Baker

(10) **Patent No.:** **US 8,830,105 B2**
(45) **Date of Patent:** **Sep. 9, 2014**

(54) **QUANTIZING CIRCUITS WITH VARIABLE PARAMETERS**

(75) Inventor: **R. Jacob Baker**, Boise, ID (US)

(73) Assignee: **Micron Technology, Inc.**, Boise, ID (US)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 142 days.

(21) Appl. No.: **13/342,844**

(22) Filed: **Jan. 3, 2012**

(65) **Prior Publication Data**

US 2012/0098691 A1 Apr. 26, 2012

Related U.S. Application Data

(63) Continuation of application No. 12/436,003, filed on May 5, 2009, now Pat. No. 8,089,387, which is a continuation of application No. 11/820,011, filed on Jun. 15, 2007, now Pat. No. 7,538,702.

(51) **Int. Cl.**

H03M 1/12 (2006.01)
H03M 1/60 (2006.01)
G11C 16/26 (2006.01)
G11C 11/56 (2006.01)
H03K 3/0231 (2006.01)

(52) **U.S. Cl.**

CPC **H03M 1/60** (2013.01); **G11C 16/26** (2013.01); **G11C 11/5642** (2013.01); **H03K 3/0231** (2013.01)
USPC **341/155**; 341/118; 341/120; 341/156; 341/164; 341/167

(58) **Field of Classification Search**

USPC 341/118–121, 155, 167, 159, 164, 165
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

5,600,319	A	2/1997	Ginetti	
5,614,856	A	3/1997	Wilson et al.	
5,659,315	A	8/1997	Mandl	
5,877,715	A *	3/1999	Gowda et al.	341/122
5,953,276	A	9/1999	Baker	
6,044,019	A	3/2000	Cernea et al.	
6,188,340	B1	2/2001	Matsumoto et al.	
6,204,795	B1	3/2001	Afghahi	
6,282,120	B1	8/2001	Cernea et al.	
6,490,200	B2	12/2002	Cernea et al.	
6,504,750	B1	1/2003	Baker	
6,567,297	B2	5/2003	Baker	
6,661,708	B2	12/2003	Cernea et al.	
6,664,708	B2	12/2003	Shlimak et al.	
6,665,013	B1	12/2003	Fossum	
6,670,904	B1 *	12/2003	Yakovlev	341/167
6,741,502	B1	5/2004	Cernea	

(Continued)

OTHER PUBLICATIONS

Rane Corporation, RaneNote 137, "Digital Charma of Audio A/D Converters," 1997, 12 pgs.

(Continued)


Primary Examiner — Linh Nguyen

(74) Attorney, Agent, or Firm — Fletcher Yoder, P.C.

(57) **ABSTRACT**

Systems, methods, and devices for obtaining data from a data location. The method may include generating a first value by sensing a data location under a first condition and generating a second value by sensing the data location under a second condition. The method may further include combining the first value with the second value to identify data conveyed by the data location.

20 Claims, 21 Drawing Sheets



(56)

References Cited

U.S. PATENT DOCUMENTS

6,781,906 B2 8/2004 Perner et al.
 6,785,156 B2 8/2004 Baker
 6,795,359 B1 9/2004 Baker
 6,798,705 B2 9/2004 Baker
 6,807,403 B2 10/2004 Tanaka
 6,813,208 B2 11/2004 Baker
 6,822,892 B2 11/2004 Baker
 6,826,102 B2 11/2004 Baker
 6,829,188 B2 12/2004 Baker
 6,847,234 B2 1/2005 Choi
 6,850,441 B2 2/2005 Mokhlesi et al.
 6,856,564 B2 2/2005 Baker
 6,870,784 B2 3/2005 Baker
 6,901,020 B2 5/2005 Baker
 6,914,838 B2 7/2005 Baker
 6,930,942 B2 8/2005 Baker
 6,954,390 B2 10/2005 Baker
 6,954,391 B2 10/2005 Baker
 6,977,601 B1 12/2005 Fletcher et al.
 6,985,375 B2 1/2006 Baker
 7,002,833 B2 2/2006 Hush et al.
 7,009,901 B2 3/2006 Baker
 7,023,369 B2* 4/2006 Bocko et al. 341/143
 7,061,324 B2 6/2006 Diorio et al.
 7,095,667 B2 8/2006 Baker
 7,102,932 B2 9/2006 Baker
 7,133,307 B2 11/2006 Baker
 7,321,329 B2* 1/2008 Tooyama et al. 341/163
 7,366,021 B2 4/2008 Taylor
 7,369,168 B2* 5/2008 Beck et al. 348/308
 7,471,230 B2* 12/2008 Tooyama et al. 341/164
 7,485,836 B2* 2/2009 Altice et al. 250/208.1
 7,538,702 B2 5/2009 Baker
 7,567,280 B2* 7/2009 Muramatsu et al. 348/294
 7,623,173 B2* 11/2009 Nitta et al. 348/302
 7,642,947 B2* 1/2010 Suzuki et al. 341/169
 7,671,317 B2* 3/2010 Shimomura et al. 250/208.1
 7,683,817 B2* 3/2010 Murata et al. 341/158
 7,705,897 B2 4/2010 Muramatsu
 2002/0101758 A1 8/2002 Baker
 2002/0194557 A1 12/2002 Park
 2003/0039162 A1 2/2003 Baker
 2003/0043616 A1 3/2003 Baker
 2003/0067797 A1 4/2003 Baker
 2003/0198078 A1 10/2003 Baker
 2003/0214868 A1 11/2003 Baker
 2004/0008555 A1 1/2004 Baker
 2004/0032760 A1 2/2004 Baker
 2004/0062100 A1 4/2004 Baker
 2004/0076052 A1 4/2004 Baker
 2004/0095839 A1 5/2004 Baker
 2004/0190327 A1 9/2004 Baker
 2004/0190334 A1 9/2004 Baker
 2004/0199710 A1 10/2004 Baker
 2004/0240294 A1 12/2004 Baker
 2005/0002249 A1 1/2005 Baker
 2005/0007803 A1 1/2005 Baker
 2005/0007850 A1 1/2005 Baker
 2005/0013184 A1 1/2005 Baker
 2005/0018477 A1 1/2005 Baker
 2005/0018512 A1 1/2005 Baker
 2005/0041128 A1 2/2005 Baker
 2005/0088892 A1 4/2005 Baker

2005/0088893 A1 4/2005 Baker
 2005/0201145 A1 9/2005 Baker
 2005/0206548 A1* 9/2005 Muramatsu et al. 341/172
 2006/0013040 A1 1/2006 Baker
 2006/0062062 A1 3/2006 Baker
 2006/0221696 A1 10/2006 Li
 2006/0227641 A1 10/2006 Baker
 2006/0232676 A1* 10/2006 Boemler 348/172
 2006/0250853 A1 11/2006 Taylor et al.
 2006/0291291 A1 12/2006 Hosono et al.
 2008/0309530 A1 12/2008 Baker
 2009/0212984 A1 8/2009 Baker
 2009/0261998 A1* 10/2009 Chae et al. 341/118

OTHER PUBLICATIONS

Baker, R.J., (2001-2006) *Sensing Circuits for Resistive Memory*, presented at various universities and companies.
 Baker, "CMOS Mixed Signal Circuit Design," IEEE Press, A. John Wiley & Sons, Inc.; Copyright 2003, Figures 30.63, 31.82, 32.6, 32.7, 32.24, 32.51, 33.34, 33.47, 33.51, 34.18, 34.24; located at <http://cmosedu.com/cmos2/book2.htm>.
 Dallas Semiconductor, Maxim Application Note 1870, "Demystifying Sigma-Delta ADCs," (Jan. 31, 2003), 15 pgs.
 Baker, R.J., (2003) *Mixed-Signal Design in the Microelectronics Curriculum*, IEEE University/Government/Industry Microelectronics (UGIM) Symposium, Jun. 30-Jul. 2, 2003.
 Baker, R.J. (2004) Delta-Sigma Modulation for Sensing, *IEEE/EDS Workshop on Microelectronics and Electron Devices (WMED)*, Apr. 2004.
 Baker, "CMOS Circuit Design, Layout, and Simulation," Second Edition, IEEE Press, A. John Wiley & Sons, Inc.; Copyright 2005; Chapters 13, 16, 17, 20, 22-24, 28-29; pp. 375-396, 433-522, 613-656, 711-828, 931-1022.
 Hadrick, M. and Baker, R.J., (2005) *Sensing in CMOS Imagers using Delta-Sigma Modulation*, a general presentation of our work in this area.
 Baker, R.J. (2005) Design of High-Speed CMOS Op-Amps for Signal Processing, *IEEE/EDS Workshop on Microelectronics and Electron Devices (WMED)*, Apr. 2005.
 Leslie, M.B., and Baker, R.J., (2006) "Noise-Shaping Sense Amplifier for MRAM Cross-Point Arrays," *IEEE Journal of Solid State Circuits*, vol. 41, No. 3, pp. 699-704.
 Duvvada, K., Saxena, V., and Baker, R. J., (2006) *High Speed Digital Input Buffer Circuits*, proceedings of the IEEE/EDS Workshop on Microelectronics and Electron Devices (WMED), pp. 11-12, Apr. 2006.
 Saxena, V., Plum, T.J., Jessing, J.R., and Baker, R. J., (2006) *Design and Fabrication of a MEMS Capacitive Chemical Sensor System*, proceedings of the IEEE/EDS Workshop on Microelectronics and Electron Devices (WMED), pp. 17-18, Apr. 2006.
 Baker, R.J. and Saxena, V., (2007) *Design of Bandpass Delta Sigma Modulators: Avoiding Common Mistakes*, presented at various universities and companies.
 Wikipedia—definition of "Error detection and correction", pulled from website Jun. 1, 2007, 9 pgs.
 Wikipedia—definition of "Hamming code", pulled from website Jun. 1, 2007, 8 pgs.
 Wikipedia—definition of "Linear feedback shift register (LFSR)", pulled from website Jun. 1, 2007, 4 pgs.
 Park, "Motorola Digital Signal Processors—Principles of Sigma-Delta Modulation for Analog-to-Digital Converters,"(Undated).

* cited by examiner




FIG. 1





FIG. 4

FIG. 2






FIG. 5





FIG. 6








FIG. 7








FIG. 10








FIG. 13

FIG. 14






FIG. 15









FIG. 18






FIG. 19








FIG. 22







**FIG. 24**




FIG. 25

QUANTIZING CIRCUITS WITH VARIABLE PARAMETERS

CROSS-REFERENCE TO RELATED APPLICATION

This application is a continuation of U.S. patent application Ser. No. 12/436,003, which was filed on May 5, 2009, now U.S. Pat. No. 8,089,387, which issued on Jan. 3, 2012, which is a continuation of U.S. patent application Ser. No. 11/820,011, which was filed on Jun. 15, 2007, now U.S. Pat. No. 7,538,702, which issued on May 26, 2009.

BACKGROUND

1. Field of Invention

Embodiments of the present invention relate generally to memory devices and, more specifically, in a particular embodiment, to quantizing circuits with variable reference signals.

2. Description of Related Art

Generally, memory devices include an array of memory elements and associated sense amplifiers. The memory elements store data, and the sense amplifiers read the data from the memory elements. To read data, for example, a current is passed through the memory element, and the current or a resulting voltage is sensed by the sense amplifier. Conventionally, the sense amplifier senses the current or voltage by comparing it to a reference current or voltage. Depending on whether the current or voltage is greater than the reference, the sense amplifier outputs a value of one or zero. That is, the sense amplifier quantizes the analog signal from the memory element into one of two logic states.

Many types of memory elements are capable of assuming more than just two states. For example, some memory elements are capable of multi-bit (e.g., more than two state) storage. For instance, rather than outputting either a high or low voltage, the memory element may output four or eight different voltage levels, each level corresponding to a different data value. However, conventional sense amplifiers often fail to distinguish accurately between the additional levels because the difference between the levels (e.g., a voltage difference) in a multi-bit memory element is often smaller than the difference between the levels in a single-bit (i.e., two state) memory element. Thus, conventional sense amplifiers often cannot read multi-bit memory elements. This problem may be increased as high performance multi-bit memory elements become increasingly dense, thereby reducing the size of the memory elements and the difference between the levels (e.g., voltage) to be sensed by the sense amplifiers.

A variety of factors may tend to prevent the sense amplifier from discerning small differences in the levels of a multi-bit memory element. For instance, noise in the power supply, ground, and reference voltage may cause an inaccurate reading of the memory element. The noise may have a variety of sources, such as temperature variations, parasitic signals, data dependent effects, and manufacturing process variations. This susceptibility to noise often leads a designer to reduce the number of readable states of the memory element, which tends to reduce memory density and increase the cost of memory.

Conventional sense amplifiers present similar problems in imaging devices. In these devices, an array of light sensors output a current or voltage in response to light impinging upon the sensor. The magnitude of the current or voltage typically depends upon the intensity of the light. Thus, the capacity of the sense amplifier to accurately convert the cur-

rent or voltage into a digital signal may determine, in part, the fidelity of the captured image. Consequently, noise affecting the sense amplifier may diminish the performance of imaging devices.

BRIEF DESCRIPTION OF DRAWINGS

FIG. 1 illustrates an electronic device in accordance with an embodiment of the present invention;

FIG. 2 illustrates a memory device in accordance with an embodiment of the present invention;

FIG. 3 illustrates a memory array in accordance with an embodiment of the present invention;

FIG. 4 illustrates a memory element in accordance with an embodiment of the present invention;

FIG. 5 illustrates I-V traces of memory elements storing different values, in accordance with an embodiment of the present invention;

FIG. 6 illustrates noise in the bit-line current during a read operation;

FIG. 7 illustrates a quantizing circuit in accordance with an embodiment of the present invention;

FIG. 8 illustrates a delta-sigma sensing circuit in accordance with an embodiment of the present invention;

FIGS. 9 and 10 illustrate current flow during operation of the quantizing circuit of FIG. 8;

FIGS. 11-13 illustrate voltages in the quantizing circuit of FIG. 8 when sensing small, medium, and large currents, respectively;

FIG. 14 is a graph of bit-line current versus counter output for the quantizing circuit of FIG. 8;

FIG. 15 is a graph of count versus quantizing circuit output in accordance with an embodiment of the present invention;

FIG. 16 illustrates an example of a delta-sigma modulator with a variable reference signal in accordance with an embodiment of the present invention;

FIG. 17 illustrates voltages in the delta-sigma modulator of FIG. 16;

FIG. 18 illustrates I-V traces of memory elements storing different values in accordance with an embodiment of the present invention;

FIG. 19 is a flowchart illustrating the operation of the delta-sigma modulator of FIG. 16;

FIG. 20 illustrates an example of a delta-sigma modulator configured to read data from a floating-gate transistor by varying a gate voltage of the floating-gate transistor;

FIG. 21 illustrates I-V traces of floating-gate transistors storing different values over a range of gate voltages;

FIG. 22 is a flow chart illustrating the operation of the delta-sigma modulator of FIG. 20;

FIG. 23 illustrates an example of a delta-sigma modulator configured to vary both a reference voltage and a gate voltage when reading data;

FIG. 24 is a flow chart illustrating the operation of the delta-sigma modulator of FIG. 23; and

FIG. 25 illustrates an example of a system that includes the electronic device of FIG. 2.

DETAILED DESCRIPTION OF SPECIFIC EMBODIMENTS

Various embodiments of the present invention are described below. In an effort to provide a concise description of these embodiments, not all features of an actual implementation are described in the specification. It should be appreciated that in the development of any such actual implementation, as in any engineering or design project, numerous

implementation-specific decisions must be made to achieve the developers' specific goals, such as compliance with system-related and business-related constraints, which may vary from one implementation to another. Moreover, it should be appreciated that such a development effort might be complex and time consuming but would nevertheless be a routine undertaking of design, fabrication, and manufacture for those of ordinary skill having the benefit of this disclosure.

Some of the subsequently described embodiments may address one or more of the problems with conventional sense amplifiers discussed above. Some embodiments include a quantizing circuit configured to detect small differences in voltages and/or currents. As explained below, the quantizing circuit may sample the measured electrical parameter on multiple occasions and filter, e.g., average or sum, the samples to reduce the impact of noise. As a result, in some embodiments, the quantizing circuit may resolve small differences between voltage or current levels in multi-bit memory elements and/or light sensors, which may allow circuit designers to increase the number of bits stored per memory element and/or the sensitivity of an imaging device. Prior to describing these embodiments and their advantages, the environment in which they may operate is described.

FIG. 1 depicts an electronic device 10 that may be fabricated and configured in accordance with one or more of the present embodiments. The illustrated electronic device 10 includes a memory device 12 that, as explained further below, may include multi-bit memory elements and quantizing circuits. Alternatively, or additionally, the electronic device 10 may include an imaging device 13 having the quantizing circuits.

Myriad devices may embody one or more of the present techniques. For example, the electronic device 10 may be a storage device, a communications device, an entertainment device, an imaging system, or a computer system, such as a personal computer, a server, a mainframe, a tablet computer, a palm-top computer, or a laptop.

FIG. 2 depicts a block diagram of an embodiment of the memory device 12. The illustrated memory device 12 may include a memory array 14, a quantizing circuit 16, a column decoder 18, a column address latch 20, row drivers 22, a row decoder 24, row address latches 26, and control circuitry 28. As described below with reference to FIG. 3, the memory array 14 may include a matrix of memory elements arranged in rows and columns. As will be appreciated, the imaging device 13 (FIG. 1) may include similar features except that in the case of an imaging device 13, the array 14 might comprise an array of imaging elements, such as complementary-metal-oxide semiconductor (CMOS) imaging elements or charge coupled devices (CCDs).

When accessing the memory elements, the control circuitry may receive a command to read from or write to a target memory address. The control circuitry 28 may then convert the target address into a row address and a column address. In the illustrated embodiment, the row address bus 30 transmits the row address to the row address latches 26, and a column address bus 32 transmits column address to the column address latches 20. After an appropriate settling time, a row address strobe (RAS) signal 34 (or other controlling clock signal) may be asserted by the control circuitry 28, and the row address latches 26 may latch the transmitted row address. Similarly, the control circuitry 28 may assert a column address strobe 36, and the column address latches 20 may latch the transmitted column address.

Once row and column addresses are latched, the row decoder 24 may determine which row of the memory array 14 corresponds to the latched row address, and the row drivers 22

may assert a signal on the selected row. Similarly, the column decoder 18 may determine which column of the memory array 14 corresponds with the latched column address, and the quantizing circuit 16 may quantize a voltage or current on the selected column. Additional details of reading and writing are described below.

FIG. 3 illustrates an example of a memory array 14. The illustrated memory array 14 includes a plurality of bit-lines 38, 40, 42, 44, and 46 (also referred to as BL0-BL4) and a plurality of word-lines 48, 50, 52, 54, 56, 58, 60, and 62 (also referred to as WL0-WL7). These bit-lines and word-lines are examples of electrical conductors. The memory array 14 further includes a plurality of memory elements 64, each of which may be arranged to intersect one of the bit-lines and one of the word-lines. In other embodiments, imaging elements may be disposed at each of these intersections.

The memory elements and imaging elements may be referred to generally as data locations, i.e., devices or elements configured to convey data, either stored or generated by a sensor, when sensed by a sensing circuit, such as the quantizing circuits discussed below. The data locations may be formed on an integrated semiconductor device (e.g., a device formed on a single crystal of silicon) that also includes the other components of the memory device 12 (or imaging device 13).

In some embodiments, the illustrated memory elements 64 are flash memory devices. The operation of the flash memory elements is described further below with reference to the FIGS. 4 and 5. It should be noted that, in other embodiments, the memory elements 64 may include other types of volatile or nonvolatile memory. For example, the memory elements 64 may include a resistive memory, such as a phase change memory or magnetoresistive memory. In another example, the memory elements 64 may include a capacitor, such as a stacked or trench capacitor. Some types of memory elements 64 may include an access device, such as a transistor or a diode associated with each of the memory elements 64, or the memory elements 64 may not include an access device, for instance in a cross-point array.

FIG. 4 illustrates a circuit 66 that models the operation of an arbitrarily selected memory element 64, which is disposed at the intersection of WL3 and BL0. This circuit 66 includes a capacitor 68, a pre-drain resistor 70 (R_{PD}), a post-source resistor 72 (R_{PS}), and a ground 74. The resistors 70 and 72 model the other devices in series with the memory element 64 being sensed. The illustrated memory element 64 includes a gate 76, a floating gate 78, a drain 80, and a source 82. In the circuit 66, the drain 80 and source 82 are disposed in series between the pre-drain resistor 70 and the post-source resistor 72. The gate 76 is coupled to WL3. The pre-drain resistor 70, the drain 80, the source 82, and the post-source resistor 72 are disposed in series on the bit-line BL0. The capacitor 68, which models the capacitance of the bit-line, has one plate coupled to ground 74 and another plate coupled to the bit-line BL0, in parallel with the memory elements 64.

Several of the components of the circuit 66 represent phenomenon affecting the memory elements 64 when it is sensed. The pre-drain resistor 70 generally represents the drain-to-bitline resistance of the memory elements 64 coupled to the bit-line above (i.e., up current from) WL3 when these memory elements 64 are turned on, (e.g., during a read operation). Similarly, the post source resistor 72 generally corresponds to the source-to-ground resistance of the memory elements 64 coupled to the bit-line below WL3 when the memory element 64 is sensed. The circuit 66 models electrical phenomena associated with reading the memory elements 64 at the intersection of WL3 and BL0.

5

The operation of the memory elements **64** will now be briefly described with reference to FIGS. **4** and **5**. FIG. **5** illustrates one potential relationship between the bit-line current (I_{BIT}), the word-line voltage (V_{WL}), and the voltage of the floating gate **78** (V_{FG}). As illustrated by FIG. **5**, V_{FG} affects the response of the memory element **64** to a given V_{WL} . Decreasing the voltage of the floating gate shifts the I-V curve of the memory elements **64** to the right. That is, the relationship between the bit-line current and a word-line voltage depends on the voltage of the floating gate **78**. The memory elements **64** may store data by exploiting this effect.

To write data to the memory elements **64**, a charge corresponding to the data may be stored on the floating gate **78**. The charge of the floating gate **78** may be modified by applying voltages to the source **82**, drain **80**, and/or gate **76** such that the resulting electric fields produce phenomenon like Fowler-Northam tunneling and/or hot-electron injection near the floating gate **78**. Initially, the memory elements **64** may be erased by applying a word-line voltage designed to drive electrons off of the floating gate **78**. In some embodiments, an entire column or block of memory elements **64** may be erased generally simultaneously. Once the memory elements **64** are erased, the gate **76** voltage may be manipulated to drive a charge onto the floating gate **78** that is indicative of a data value. After the write operation ends, the stored charge may remain on the floating gate **78** (i.e., the memory elements **64** may store data in a nonvolatile fashion).

As illustrated by FIG. **5**, the value stored by the memory element **64** may be read by applying a voltage, V_{WL} , to the gate **76** and quantizing (e.g., categorizing) a resulting bit-line current, I_{BIT} . Each of the I-V traces depicted by FIG. **5** correspond to a different charge stored on the floating gate, V_{FG} , which should not be confused with the voltage that is applied to the gate, V_{WL} . The difference in floating gate **70** voltage, V_{FG} , between each I-V trace is an arbitrarily selected scaling factor "x." The illustrated I-V traces correspond to eight-different data values stored by the memory element **64**, with a V_{FG} of $0x$ representing a binary data value of **000**, a V_{FG} of $1x$ representing a binary data value of **001**, and so on through V_{FG} of $7x$, which represents a binary data value of **111**. Thus, by applying a voltage to the gate **76** and measuring the resulting bit-line current, the charge stored on the floating gate **78** may be sensed, and the stored data may be read.

The accuracy with which the bit-line current is quantized may affect the amount of data that a designer attempts to store in each memory element **64**. For example, in a system with a low sensitivity, a single bit may be stored on each memory element **64**. In such a system, a floating gate voltage V_{FG} of $0x$ may represent a binary value of **0**, and a floating gate voltage V_{FG} of $-7x$ may represent a binary value of one. Thus, the difference in floating gate voltages V_{FG} corresponding to different data values may be relatively large, and the resulting differences and bit-line currents for different data values may also be relatively large. As a result, even low-sensitivity sensing circuitry may discern these large differences in bit-line current during a read operation and correctly categorize the sensed voltage or current. In contrast, high-sensitivity sensing circuitry may facilitate storing more data in each memory element **64**. For instance, if the sensing circuitry can distinguish between the eight different I-V traces depicted by FIG. **5**, then the memory elements **64** may store three bits. That is, each of the eight different charges stored on the floating gate **78** may represent a different three-bit value: **000**, **001**, **010**, **011**, **100**, **101**, **110**, or **111**. Thus, circuitry that precisely quantizes the bit-line current ' I_{BIT} ' may allow a designer to increase the amount of data stored in each memory element **64**.

6

However, as mentioned above, a variety of effects may interfere with accurate measurement of the bit-line current. For instance, the position of the memory elements **64** along a bit-line may affect R_{PD} and R_{PS} , which may affect the relationship between the word-line voltage V_{WL} and the bit-line current I_{BIT} . To illustrate these effects, FIG. **6** depicts noise on the bit-line while reading from the memory element **64**. As illustrated, noise in the bit-line current I_{BIT} may cause the bit-line current I_{BIT} to fluctuate. Occasionally, the fluctuation may be large enough to cause the bit-line current I_{BIT} to reach a level that represents a different stored data value, which could cause the wrong value to be read from the memory elements **64**. For instance, if the bit-line current is sensed at time **84**, corresponding to an arbitrarily selected peak, a data value of **100** may be read rather than the correct data value of **011**. Similarly, if the bit-line current is sensed at time **86**, corresponding to an arbitrarily selected local minimum, a data value of **010** may be read rather than a data value of **011**. Thus, noise on the bit-line may cause erroneous readings from memory elements **64**.

FIG. **7** depicts a quantizing circuit **16** that may tend to reduce the likelihood of an erroneous reading. The illustrated quantizing circuit **16** includes an analog-to-digital converter **88** and a digital filter **90** coupled to each of the bit-lines **38**, **40**, **42**, **44**, and **46**, respectively. Each bit-line **38**, **40**, **42**, **44**, and **46** may connect to a different analog-to-digital converter **88** and digital filter **90**. The digital filters **90**, in turn, may connect to an input/output bus **92**, which may connect to a column decoder **18**, a column address latch **20**, and/or control circuitry **28** (see FIG. **2**).

In operation, the quantizing circuit **16** may quantize (e.g., digitize) analog signals from the memory elements **64** in a manner that is relatively robust to noise. As explained below, the quantizing circuit **16** may do this by converting the analog signals into a bit-stream and digitally filtering high-frequency components from the bit-stream.

The analog-to-digital converter **88** may be a one-bit, analog-to-digital converter or a multi-bit, analog-to-digital converter. In the present embodiment, an analog-to-digital converter **88** receives an analog signal from the memory element **64**, e.g., a bit-line current I_{BIT} or a bit-line voltage V_{BL} , and outputs a bit-stream that represents the analog signal. The bit-stream may be a one-bit, serial signal with a time-averaged value that generally represents the time-averaged value of the analog signal from the memory element **64**. That is, the bit-stream may fluctuate between values of zero and one, but its average value, over a sufficiently large period of time, may be proportional to the average value of the analog signal from the memory element **64**. In certain embodiments, the bit-stream from the analog-to-digital converter **88** may be a pulse-density modulated (PDM) version of the analog signal. The analog-to-digital converter **88** may transmit the bit-stream to the digital filter **90** on a bit-stream signal path **94**.

The digital filter **90** may digitally filter high-frequency noise from the bit-stream. To this end, the digital filter **90** may be a low-pass filter, such as a counter, configured to average (e.g., integrate and divide by the sensing time) the bit-stream over a sensing time, i.e., the time period over which the memory element **64** is sensed. (Alternatively, in some embodiments, the digital filter **90** is configured to integrate the bit-stream without dividing by the sensing time.) As a result, the digital filter **90** may output a value that is representative of both the average value of the bit-stream and the average value of the analog signal from the memory element **64**. In some embodiments, the digital filter **90** is a counter, and the cut-off frequency of the digital filter **90** may be selected by adjusting the duration of the sensing time. In the present

embodiment, increasing the sensing time will lower the cutoff frequency. That is, the frequency response of the digital filter **90** may be modified by adjusting the period of time over which the bit-stream is integrated and/or averaged before outputting a final value. The frequency response of the digital filter **90** is described further below with reference to FIG. 15. For multi-bit memory elements **64**, the output from the digital filter **90** may be a multi-bit binary signal, e.g., a digital word that is transmitted serially and/or in parallel.

Advantageously, in certain embodiments, the quantizing circuit **16** may facilitate the use of multi-bit memory elements **64**. As described above, in traditional designs, the number of discrete data values that a memory element **64** stores may be limited by sense amps that react to noise. In contrast, the quantizing circuit **16** may be less susceptible to noise, and, as a result, the memory elements **64** may be configured to store additional data. Without the high frequency noise, the intervals between signals representative of different data values may be made smaller, and the number of data values stored by a given memory element **64** may be increased. Thus, beneficially, the quantizing circuit **16** may read memory elements **64** that store several bits of data, e.g., 2, 3, 4, 5, 6, 7, 8, or more bits per memory element **64**.

Although the quantizing circuit **16** may sense the signal from the memory element **64** over a longer period of time than conventional designs, the overall speed of the memory device **12** may be improved. As compared to a conventional device, each read or write operation of the memory device **12** may transfer more bits of data into or out of the memory element **64**. As a result, while each read or write operation may take longer, more data may be read or written during the operation, thereby improving overall performance. Further, in some memory devices **12**, certain processes may be performed in parallel with a read or write operation, thereby further reducing the overall impact of the longer sensing time. For example, in some embodiments, the memory array **14** may be divided into banks that operate at least partially independently, so that, while data is being written or read from one bank, another bank can read or write data in parallel.

FIG. 8 illustrates details of one implementation of the quantizing circuit **16**. In this embodiment, the digital filter **90** is a counter, and the analog-to-digital converter **88** is a first-order delta-sigma modulator. The illustrated delta-sigma modulator **88** may include a latched comparator **96**, a capacitor **98**, and a switch **100**. In other embodiments, other types of digital filters and analog-to-digital converters may be employed, such as those described below in reference to FIGS. 17 and 18.

As illustrated, an input of the counter **90** may connect to the bit-stream signal path **94**, which may connect to an output of the comparator **96**. The output of the comparator **96** may also connect to a gate of the switch **100** by a feedback signal path **102**. The output terminal (e.g., source or drain) of the switch **100** may connect in series to one of the bit-lines **38, 40, 42, 44, or 46**, and the input terminal of the switch **100** may connect to a reference current source **104** (I_{REF}). One plate of the capacitor **98** may connect to one of the bit-lines **38, 40, 42, 44, or 46**, and the other plate of the capacitor **98** may connect to ground.

The illustrated counter **90** counts the number of clock cycles that the bit-stream **94** is at a logic high value or logic low value during the sensing time. The counter may count up or count down, depending on the embodiment. In some embodiments, the counter **90** may do both, counting up one for each clock cycle that the bit-stream has a logic high value and down one for each clock cycle that the bit-stream has a logic low value. Output terminals (D0-D5) of the counter **90** may connect to the input/output bus **92** for transmitting the

count. The counter **90** may be configured to be reset to zero or some other value when a reset signal is asserted. In some embodiments, the counter **90** may be a series connection of D-flip flops, e.g., D-flip flops having SRAM or other memory for storing an initial value and/or values to be written to the memory element **64**.

In the illustrated embodiment, the clocked comparator **96** compares a reference voltage (V_{REF}) to the voltage of one of the bit-lines **38, 40, 42, 44, or 46** (V_{BL}), which may be generally equal to the voltage of one plate of the capacitor **98**. The comparator **96** may be clocked (e.g., falling and/or rising edge triggered), and the comparison may be performed at regular intervals based on the clock signal, e.g., once per clock cycle. Additionally, the comparator **96** may latch, i.e., continue to output, values (V_{FB}) between comparisons. Thus, when the clock signals the comparator **96** to perform a comparison, if V_{BL} is less than V_{REF} , then the comparator **96** may latch its output to a logic low value, as described below in reference to FIG. 9. Conversely, if V_{BL} is greater than V_{REF} , then the comparator **96** may latch a logic high value on its output, as described below in reference to FIG. 10. As a result, the illustrated comparator **96** outputs a bit-stream that indicates whether V_{BL} is larger than V_{REF} , where the indication is updated once per clock cycle.

Advantageously, in some embodiments, the quantizing circuit **16** may include a single comparator (e.g., not more than one) for each column of multi-level memory elements **64**. In contrast, conventional sense amplifiers often include multiple comparators to read from a multi-bit memory cell, thereby potentially increasing device complexity and cost.

The capacitor **98** may be formed by capacitive coupling of the bit-lines **38, 40, 42, 44, and 46**. In other designs, this type of capacitance is referred to as parasitic capacitance because it often hinders the operation of the device. However, in this embodiment, the capacitor **98** may be used to integrate differences between currents on the bit-lines **38, 40, 42, 44, or 46** and the reference current to form the bit-stream, as explained further below. In some embodiments, the capacitor **98** may be supplemented or replaced with an integrated capacitor that provides greater capacitance than the "parasitic" bit-line capacitance.

The illustrated switch **100** selectively transmits current I_{REF} from the reference current source **104**. In various embodiments, the switch **100** may be a PMOS transistor (as illustrated in FIGS. 8-10) or an NMOS transistor (as illustrated in FIG. 17) controlled by the V_{FB} signal on the feedback signal path **102**.

The operation of the quantizing circuit **16** will now be described with reference to FIGS. 9-12. Specifically, FIGS. 9 and 10 depict current flows in the quantizing circuit **16** when the comparator **96** is latched low and high, respectively. FIG. 11 illustrates V_{BL} , the bit-stream output from the comparator **96**, and the corresponding increasing count of the counter **90** for a relatively small bit-line current. FIG. 12 depicts the same voltages when measuring a medium sized bit-line current, and FIG. 13 depicts these voltages when measuring a relatively large bit-line current.

To sense the current through the memory element **64**, the illustrated delta-sigma modulator **88** exploits transient effects to output a bit-stream representative of the bit-line current I_{BIT} . Specifically, the delta-sigma modulator **88** may repeatedly charge and discharge the capacitor **98** with a current divider that subtracts the bit-line current I_{BIT} from the reference current I_{REF} . Consequently, a large current through the memory element **64** may rapidly discharge the capacitor **98**, and a small current through the memory element **64** may slowly discharge the capacitor **98**.

To charge and discharge the capacitor **98**, the delta-sigma modulator **88** switches between two states: the state depicted by FIG. **9** (hereinafter “the charging state”) and the state depicted by FIG. **10** (hereinafter “the discharging state”). Each time the delta-sigma modulator **88** transitions between these states, the bit-stream changes from a logic high value to a logic low value or vice versa. The proportion of time that the delta-sigma modulator **88** is in the state illustrated by either FIG. **9** or FIG. **10** may be proportional to the size of the bit-line current I_{BIT} through the memory element **64**. The larger the bit-line current I_{BIT} , the more time that the delta-sigma modulator **88** is in the state illustrated by FIG. **9**, rather than the state illustrated by FIG. **10**, and the more time that the bit-stream has a logic low value.

Starting with the charging state (FIG. **9**), the capacitor **98** may initially accumulate a charge (e.g., become more charged). To this end, the output of the comparator **96** is latched to logic low, which, as mentioned above, may occur when V_{BL} is less than V_{REF} . The logic low may be conveyed to switch **100** by the feedback signal path **102**, and the switch **100** may close, thereby conducting the reference current I_{REF} through one of the bit-lines **38**, **40**, **42**, **44**, or **46**, as indicated by the larger arrows in FIG. **9**. A portion of the electrons flowing through the reference current source **104** may be accumulated by the capacitor **98**, as indicated by the smaller-horizontal arrows, and the remainder may be conducted through the memory element **64**, i.e., the bit-line current I_{BIT} , as indicated by the smaller vertical arrows. Thus, the capacitor **98** may accumulate a charge, and V_{BL} may increase.

The comparator **96** and the reference current source **104** may cooperate to charge the capacitor **98** for a discrete number of clock cycles. That is, when the delta-sigma modulator **88** transitions to the charging state, the delta-sigma modulator **88** may remain in this state for an integer number of clock cycles. In the illustrated embodiment, the comparator **96**, the output of which is latched, changes state no more than once per clock cycle, so the switch **100**, which is controlled by the output of the comparator **96**, V_{FB} , conducts current for a discrete number of clock cycles. As a result, the reference current source **104** conducts current I_{REF} through the bit-line and into the capacitor **98** for an integer number of clock cycles.

After each clock cycle of charging the capacitor **98**, the delta-sigma modulator **88** may transition from the charging state to the discharging state, which is illustrated by FIG. **10**, depending on the relative values of V_{BL} and V_{REF} . Once per clock cycle (or at some other appropriate interval, such as twice per clock cycle), the comparator **96** may compare the voltage of the capacitor V_{BL} to the reference voltage V_{REF} . If the capacitor **98** has been charged to the point that V_{BL} is greater than V_{REF} , then the output of the comparator **96** may transition to logic high, as illustrated in FIG. **10**. The logic high signal may be conveyed to the switch **100** by the feedback signal path **102**, thereby opening the switch **100**. As a result, the reference current source **104** may cease conducting current through the memory element **64** and into the capacitor **98**, and the capacitor **98** may begin to discharge through the memory element **64**.

In the present embodiment, the delta-sigma modulator **88** discharges the capacitor **98** for a discrete number of clock intervals. After each clock cycle of discharging the capacitor **98**, the delta-sigma modulator **88** compares V_{BL} to V_{REF} . If V_{BL} is still greater than V_{REF} , then the comparator **96** may continue to output a logic high signal, i.e., $V_{FB}=1$, and the switch **100** remains open. On the other hand, if enough current has flowed out of the capacitor **98** that V_{BL} is less than V_{REF} , then the comparator **96** may output a logic low signal,

i.e., $V_{FB}=0$, and the switch **100** may close, thereby transitioning the delta-sigma modulator **88** back to the charging state and initiating a new cycle.

The counter **90** may count the number of clock cycles that the delta-sigma modulator **88** is in either the charging state or the discharging state by monitoring the bit-stream signal path **94**. The bit-stream signal path **94** may transition back and forth between logic high and logic low with the output of the comparator **96**, V_{FB} , and the counter **90** may increment and/or decrement a count once per clock cycle (or other appropriate interval) based on whether the bit-stream is logic high or logic low. After the sensing time has passed, the counter **90** may output a signal indicative of the count on output terminals **D0-D5**. As explained below, the count may correspond, e.g., proportionally, to the bit-line current, I_{BIT} .

FIGS. **11-13** illustrate voltages V_{FB} and V_{BL} in the quantizing circuit **16** when reading data from a memory element **64**. Specifically, FIG. **11** illustrates a low-current case, in which the value stored by the memory element **64** is represented by a relatively low bit-line current. Similarly, FIG. **12** illustrates a medium-current case, and FIG. **13** illustrates a high-current case. In each of these figures, the ordinate of the lower trace represents the voltage of the bit-stream signal path **94**, V_{FB} , and the ordinate of the upper trace illustrates the bit-line voltage, V_{BL} . The abscissa in each of the traces represents time, with the lower trace synchronized with the upper trace, and the duration of the time axes is one sensing time **106**.

As illustrated by FIG. **11**, the counter **90** is initially preset to zero (or some other appropriate value) by applying a reset signal. In some embodiments, the delta-sigma modulator **88** may undergo a number of start-up cycles to reach steady-state operation before initiating the sensing time and resetting the counter **90**. At the beginning of the illustrated read operation, the delta-sigma modulator **88** is in the charging state, which charges the capacitor **98** and increases V_{BL} , as indicated by dimension arrow **108**. At the beginning of the next clock cycle, the comparator **96** compares the bit-line voltage to the reference voltage and determines that the bit-line voltage is greater than the reference voltage. As a result, the bit-stream signal path **94** (V_{FB}) transitions to a logic high voltage, and the delta-sigma modulator **88** transitions to the discharging state. Additionally, the counter **90** increments the count by one to account for one clock cycle of the bit-stream signal **94** holding a logic low value. Next, the charge stored on the capacitor **98** drains out through the memory element **64**, and the bit-line voltage drops until the comparator **96** determines that V_{BL} is less than V_{REF} , at which point the cycle repeats. The cycle has a period **112**, which may be divided into a charging portion **114** and a discharging portion **116**. Once during each cycle in the sensing time **106**, the count stored in the counter **90** may increase by one. At the end of the sensing time **106**, the counter **90** may output the total count.

A comparison of FIG. **11** to FIGS. **12** and **13** illustrates why the count correlates with the bit-line current. In FIG. **13**, the high-current case, the stored charge drains from the capacitor **98** quickly, relative to the other cases, because the bit-line current I_{BIT} is large and, as a result, the delta-sigma modulator **88** spends more time in the charging state than the discharging state. As a result, the bit-stream has a logic low value for a large portion of the sensing time **106**, thereby increasing the count.

The capacitance of the capacitor **98** may be selected with both the clock frequency and the range of expected bit-line currents in mind. For example, the capacitor **98** may be large enough that the capacitor **98** does not fully discharge (e.g., saturate) when the bit-line current I_{BIT} is either at its lowest

expected value or at its highest expected value. That is, in some embodiments, the capacitor **98** generally remains in a transient state while reading the memory element **64**. Similarly, the frequency at which the comparator **96** is clocked may affect the design of the capacitor **98**. A relatively high frequency clock signal may leave the capacitor **98** with relatively little time to discharge or saturate between clock cycles, thereby leading a designer to choose a smaller capacitor **98**.

Similarly, the size of the reference current may be selected with the range of expected bit-line currents in mind. Specifically, in certain embodiments, the reference current is less than the largest expected bit-line current I_{BIT} , so that, in the case of maximum bit-line current I_{BIT} , the capacitor **98** can draw charge from the reference current while the rest of the reference current flows through the memory element **64**.

FIG. **14** illustrates the relationship between the bit-line current I_{BIT} and the count for the presently discussed embodiment. As illustrated by FIG. **14**, the count corresponds with (e.g., is generally proportional to) the bit-line current I_{BIT} . This relationship is described by the following equation (Equation 1), in which N_{ST} represents the number of clock cycles during the sensing time:

$$I_{BIT}I_{REF} = \text{Count}/N_{ST}$$

Thus, in the illustrated embodiment, the count corresponds with (e.g., is indicative of) the bit-line current I_{BIT} , which corresponds with the value stored by the memory element **64**.

Advantageously, the quantizing circuit **16** may quantize (e.g., categorize) the bit-line current I_{BIT} as falling into one of a large number of categories, each of which is represented by an increment of the count. In doing so, in some embodiments, the quantizing circuit **16** may resolve small differences in the bit-line current I_{BIT} . The resolution of the quantizing circuit **16** may be characterized by the following equation (Equation 2), in which I_{MR} represents the smallest resolvable difference in bit-line current I_{BIT} , i.e., the resolution of the quantizing circuit **16**:

$$I_{MR} = I_{REF}N_{ST}$$

Thus, the resolution of the quantizing circuit **16** may be increased by increasing the sensing time or the clock frequency or by decreasing I_{REF} , which may limit the maximum cell current since I_{MR} is less than I_{REF} .

The resolution of the quantizing circuit **16** may facilitate storing multiple bits in the memory element **64** or sensing multiple levels of light intensity in an image sensor element. For example, if the quantizing circuit **16** is configured to quantize (e.g., categorize) the bit-line current I_{BIT} into one of four different levels, then the memory element **64** may store two-bits of data or, if the quantizing circuit **16** is configured to categorize the bit-line current I_{BIT} into one of eight different current levels, then the memory element **64** may store three-bits of data. For the present embodiment, the number of bits stored by the memory element **64** may be characterized by the following equation (Equation 3), in which N_B represents the number of bits stored by a memory element **64** and I_{RANGE} represents the range of programmable bit-line currents through the memory element **64**:

$$N_B = \log(I_{RANGE}/I_{MR})/\log 2$$

In short, in the present embodiment, greater resolution translates into higher density data storage for a given memory element **64**.

FIG. **15** is a graph that illustrates one way in which the counter **90** may be configured to further reduce the effects of noise. In FIG. **15**, the abscissa represents the count, and the ordinate represents the output of the quantizing circuit **16**. In

the present embodiment, the three-least-significant digits of the count are disregarded as potentially corrupted by noise. That is, D0-D2 (FIG. **8**) either do not connect to the input/output bus **92** or are not interpreted as conveying data that is stored by the memory element **64**. As a result, a range of counter values may represent a single data value stored by the memory element **64**. For example, in the present embodiment, count values ranging from 00 1000 to 00 1111 are construed as representing a data value of 001. Representing data in this manner may further reduce the effects of noise because, even if noise affects the count, in many embodiments, it would have to affect the count in a consistent manner over a substantial portion of the sensing time to affect the more significant digits of the count. That is, disregarding less significant digits may lower the cutoff frequency of the counter **90**. In other embodiments, fewer, more, or no digits may be truncated from the count as potentially representing noise.

Truncating less significant digits may introduce a rounding error, or a downward bias, in the output. This effect may be mitigated by presetting (e.g., driving latches to a particular state in advance of counting or storing a value in memory) the counter **90** in a manner that accounts for this bias. The counter **90** may be preset either before reading from the memory element **64** or before writing to the memory element **64**. In some embodiments, the preset value may be one-half of the size of the range of counter values that represent a single output value. In other words, if m digits are truncated from the output, then the counter **90** may be preset to one-half of 2^m before reading from a memory element **64** or before writing to the memory element **64**. In some embodiments, the memory in the counter **90** may store this preset value.

In some of the previously described embodiments, the reference voltage V_{REF} is generally constant while sensing the data location **64**. This is not necessarily the case in the embodiment of FIG. **16**, which illustrates an example of a quantizing circuit **120** with a varying reference voltage V_{REF} . Quantizing circuit **120** may read data by sensing the data location **64** under changing conditions, e.g., different bit-line voltages V_{BL} , which may be altered by changing the reference voltage V_{REF} . (Varying a parameter, such as a voltage or current results in a change in, or different, conditions.) As described below, the response of the data location **64** to each condition, as well as the change in its response to each change in conditions, may convey information about stored data. Further, this information may be aggregated to improve the precision with which the quantizing circuit **120** writes to, and reads from, the data location **64**. These features are described further below, after the components and operation of the quantizing circuit **120** are described.

The illustrated quantizing circuit **120** includes the features of the previously described quantizing circuit **16** (FIG. **8**) along with some additional components. Among the additional components are a controller **122** and an interfuser **124**, e.g., a component configured to identify a quantity (e.g., a charge on a floating gate) based on multiple measurements indicative of that quantity. Specific examples of how the interfuser **124** may combine measurements are described below.

These additional components **122** and **124** may communicate with other portions of the quantizing circuit **120**. In the present embodiment, the controller **122** communicates with three other components: an inverting input of the comparator **96** via a reference signal path **126**, an input of the counter **90** via a reset signal path **128**, and an input of the interfuser **124** via a state signal path **130**. The illustrated interfuser **124** may connect (e.g., directly or indirectly) to both the counter **90** and

the input/output bus **92** via a plurality of digit signal paths labeled **D0-D5**. Other embodiments may include more or fewer digit signal paths. In some embodiments, the number of digit signal paths coupling the interfuser **124** to the counter **90** may be different (i.e., less or more) than the number of digit signal paths coupling the interfuser **124** to the input/output bus **92**.

Like some of the previously described embodiments, the components of the illustrated quantizing circuit **120** may be formed on an integrated semiconductor device. However, in some embodiments, one or more of the components of the illustrated quantizing circuit **120** may be disposed on another chip or device.

The illustrated controller **122** may be configured to coordinate the operation of the quantizing circuit **120**. For example, the controller **122** may vary a parameter, such as the reference voltage V_{REF} applied to the inverting input of the comparator **96**. In some embodiments, the controller **122** may vary V_{REF} according to a process described below in reference to FIG. **19**. When V_{REF} changes, the controller **122** may also signal the interfuser **124** on the state signal path **130**, thereby indicating that the quantizing circuit **120** is sensing the data location **64** under a different set of conditions. In certain embodiments, when sending the state change signal, the controller **122** may also transmit a reset signal to the counter **90**, which may cause the counter **90** to shift its count to the interfuser **124** and reset the count. Specific sequences of these signals are described below.

The operation of the quantizing circuit **120** will now be described with reference to the following figures: FIG. **17**, which illustrates voltages in the quantizing circuit over time; FIG. **18**, which illustrates the response of a floating-gate transistor to different source-to-drain voltages and floating gate charges; and FIG. **19**, which illustrates a process for using data from FIG. **17** to identify a floating gate charge in FIG. **18**.

As noted, FIG. **17** illustrates voltages in the quantizing circuit **120** when reading data from the data location **64**. Specifically, the top portion of FIG. **17** illustrates the bit-line voltage V_{BL} over time, and the lower trace illustrates the complement of the feedback voltage V_{FB} (i.e., the bit-stream) over time. In the figure, the illustrated time period is divided into two portions: a first sensing time **132** and a second sensing time **134**. Between these two time periods **132** and **134**, the reference voltage V_{REF} changes from a low reference voltage to a high reference voltage. Within a time period **132** or **134**, in this embodiment, the reference voltage is generally constant. The change in the reference voltage V_{REF} may be larger than it appears in the figure. To depict variation in the bit-line voltage V_{BL} , the difference between $V_{REF-LOW}$ and $V_{REF-HIGH}$ is compressed.

With the exception of the change in reference voltage V_{REF} , the traces illustrated by FIG. **17** are similar to those discussed above with reference to FIGS. **11-13**. As previously described, the delta-sigma modulator **88** (FIG. **16**) may attempt to keep the bit-line voltage V_{BL} above the reference voltage V_{REF} by elevating the feedback voltage V_{FB} whenever the bit-line voltage V_{BL} is less than the reference voltage V_{REF} . As described, elevating the feedback voltage V_{FB} (or its complement, in some embodiments) turns on the current switch **100**, and as a result, the reference current I_{REF} flows into the bit-line, thereby elevating its voltage V_{BL} . Thus, the ratio of the sensing time that V_{BL} is high is proportional to the current leaving the bit-line I_{BIT} through the data location **64**.

In this embodiment, when V_{REF} increases, the set-point of the delta-sigma modulator **88** changes and V_{BL} rises, thereby driving more current I_{BIT} through the data location **64** to

ground **74**. As a result, in this embodiment, the count accumulates faster during the second sensing time **134** than during the first sensing time **132**, because a higher V_{REF} leads to a higher V_{BL} , which drives a larger bit-line current I_{BIT} to ground **74**. A larger I_{BIT} may cause V_{FB} to remain at logic high for more time to accommodate the larger bit-line current I_{BIT} , and the count may accumulate faster.

The change that results from changing V_{REF} may depend on the type of data location and its state. An example of the relationship between bit-line current I_{BIT} and bit-line voltage V_{BL} is illustrated by FIG. **18**. In this embodiment, the data location **64** is a floating-gate transistor, so higher source-to-drain voltages V_{BL} may tend to produce larger currents through the data location **64** I_{BIT} . This effect may depend, in part, on the charge on the floating gate V_{FG} , as indicated by the eight-different traces, corresponding to eight-different floating gate charges, labeled $0x$ through $-7x$, where x is an arbitrarily selected scaling constant.

For each of the traces, both the current at a given voltage and the overall shape of the trace may be distinct from the other traces. For example, in the trace corresponding to a floating gate charge of $-6x$, $V_{REF-LOW}$ produces a bit-line current I_1 , and $V_{REF-HIGH}$ produces a bit-line current I_2 . Not only are both of these currents I_1 and I_2 , considered alone, different from the I_{BIT} through transistors with different V_{FG} at the same V_{BL} , the relationship between I_1 and I_2 is also different for each V_{FG} . Specifically, in this embodiment, the slope of each trace changes depending on V_{FG} . Thus, in this embodiment, given the two coordinates represented by I_1 and I_2 , each trace has three distinguishing characteristics: the value of I_1 , the value of I_2 , and the slope from $V_{REF-LOW}$ to $V_{REF-HIGH}$. This additional information about the response of the data location **64** to different voltages can be used to identify the floating gate charge and, thereby, read data.

In some embodiments, the quantizing circuit **120** may read data by performing a sensing process **140** illustrated by FIG. **19**. The illustrated process **140** begins with determining a first value by sensing a data location at a first voltage, as illustrated by block **142**. In certain embodiments, determining the first value may include holding the data location **64** (FIG. **16**) at a first voltage $V_{REF-LOW}$ with the delta-sigma modulator **88** and determining a first count (hereinafter referred to as C_1) based on a bit-stream output from the delta-sigma modulator **88**.

After C_1 is generated, the controller **124** may signal the interfuser **124** to latch the output of the counter **90** and, thereby, receive the first value. Thus, the interfuser **124** may include memory. Also, in some embodiments, the controller **122** may reset the counter **90** to prepare the counter to generate a second value under different conditions.

Next in the process **140**, a second value is generated by sensing the data location at a second voltage, as illustrated by block **144**. The second value may be a count (referred to as C_2) from the delta-sigma modulator **88** (FIG. **16**). In some embodiments, the second voltage may be different from the first voltage, e.g., higher, or lower. For instance, the second voltage may be $V_{REF-HIGH}$.

The second value may be generated generally consecutively with, e.g., immediately after, determining the first value. However, in some embodiments, there may be a waiting period between determining the first value and the second value. For example, the controller **122** in the quantizing circuit **120** (FIG. **16**) may delay the start of the second count while the delta-sigma modulator **88** reaches steady state operation under the new reference voltage, $V_{REF-HIGH}$. In other embodiments, the second value may be added to the first value, and the counter **90** may continue counting as the reference voltage V_{REF} changes.

15

After determining the first value and the second value, they may be combined to identify data stored by the data location, as illustrated by block 146 (FIG. 19). Combining these values may include applying the values to a data fusion algorithm, i.e., an algorithm that generates a single output value based on two or more input values. An example is described below in reference to the quantizing circuit 120 of FIG. 16.

After the second count C_2 is generated, the controller 122 may signal the interfuser 124 to latch the outputs of the counter 90 and receive the second count C_2 , and this second value may be combined with the first value to identify the data stored by the data location 64. In some embodiments, the interfuser 124 may combine the first value with its second value according to an equation. That is, the data may be a function of C_1 and C_2 , which are sensed under different conditions. Below, is an example of such an equation (Equation 4), in which E_1 , E_2 , and E_3 are empirically or analytically determined constants:

$$\text{Data} = E_1 \cdot C_1 + E_2 \cdot C_2 + E_3 (C_2 - C_1) / (V_{REF-HIGH} - V_{REF-LOW})$$

The constants E_1 , E_2 , and E_3 may be determined by testing or modeling the operation of a data location. The constants E_1 , E_2 , and E_3 may be selected to minimize the likelihood of an erroneous reading. By changing these values, different weights may be attached to different terms depending on its descriptive strength. In some embodiments, $V_{REF-HIGH}$ and $V_{REF-LOW}$ may be generally fixed or constant, and the reciprocal of their difference may be incorporated into the constant E_3 .

In other embodiments, a variety of other equations or sensor fusion techniques may be employed to identify the stored data. Examples of other types of sensor fusion algorithms include a Kalman filter, a Bayesian network, or a neural network.

In some embodiments, additional values may be generated by sensing the data location 64 at other voltages. For instance, a third value may be generated at a third voltage, and a fourth value may be generated at a fourth voltage. These additional values may be combined with the first and the second values to identify data stored by the data location.

Other embodiments may read data by applying multiple stimuli to different kinds of data locations. For instance, the data location 64 may be a photo-diode, a CCD device, a CMOS image sensor, a phase change memory, a magneto-resistive memory, or other type of resistive memory.

The illustrated process 140 may combine the separate values to identify the stored data with greater precision than with an individual value. For example, sensing the floating-gate transistor characterized in FIG. 18 at two different voltages may provide more information to select among the traces illustrated by FIG. 18 and determine the best-fit profile. Thus, by measuring a profile of the data location 64 (i.e., the response of the data location to a stimulus under changing conditions), the state of the data location can be identified with greater fidelity, and the stored data can be read more precisely.

While some of the embodiments described above vary the source-to-drain voltage of a floating-gate transistor, other embodiments may vary other parameters, such as the gate-to-source voltage. FIG. 20 illustrates an example of such a quantizing circuit 148. As described below, the illustrated quantizing circuit 148 may read data from the floating-gate transistor 150 by sensing a response of the floating-gate transistor 150 to two or more different gate voltages.

The illustrated quantizing circuit 148 includes a controller 152 that connects to the interfuser 124 via the state signal path

16

130, the counter 90 via the reset signal path 128, and the gate of the floating-gate transistor 150 via a word line 154. Like several of the other embodiments described herein, both the controller 152 and the other components of the quantizing circuit 148 may be formed on an integrated semiconductor device, for example, or these components may be formed on separate chips, for example in a multi-chip module or on a printed circuit board.

The operation of the quantizing circuit 148 will now be described with reference to both FIG. 21, which illustrates the relationship of the gate-to-source voltage (V_{GS}) of the floating-gate transistor 150 to the bit-line current I_{BIT} for eight-different values stored on the floating gate of the floating-gate transistor 150, and FIG. 22, which is a flow chart depicting an example of a process for reading data from the floating-gate transistor 150.

FIG. 21 illustrates I-V traces for a variety of data values stored by the floating-gate transistor 150, e.g., different quanta of charge on its floating gate. The ordinate of FIG. 21 represents the bit-line current I_{BIT} , and the abscissa of FIG. 21 represents the voltage between the gate of the floating-gate transistor 150 and the source of the floating-gate transistor 150 V_{GS} . In the illustrated embodiment, the source of the floating-gate transistor 150 is coupled to ground 74, so V_{GS} may be approximately equal to the voltage of the word line 154, which as described below, may be controlled by the controller 152.

As mentioned, FIG. 22 illustrates an example of a reading process 156, which may be executed by certain embodiments of the quantizing circuit 148 (FIG. 20). The illustrated process 156 begins with sensing a first value by sensing a data location at a first gate voltage, as illustrated by block 158. (As used herein, the word "sensing" is distinguished from the word "reading" in that reading includes identifying stored data whereas sensing includes merely measuring or quantifying some parameter, which may correspond to stored data, either directly or indirectly, and which may be used to read stored data, either directly or through subsequent processing, e.g., through Equation 4 above.) Sensing a first value may include sensing a response of the floating-gate transistor 150 to a gate voltage that generally corresponds to V_{WL-LOW} in FIG. 21. In some embodiments, V_{WL-LOW} may be generally equal to ground 74.

Sensing the first value may include resetting the counter 90 by asserting the reset signal 128 and signaling the interfuser 124 that the first value is being sensed by asserting a signal on the state signal path 130. For example, the controller 168 may signal the interfuser 124 to latch a count from the counter 90 at the end of a first sensing time. At the end of the first sensing time, the count of the counter 90 may generally correspond to the first value.

Next in the process 156 (FIG. 22), a second value of may be sensed by sensing a data location at a second gate voltage, as illustrated by block 160. The second gate voltage may be different from the first gate voltage, as illustrated by FIG. 21. As illustrated, the second gate voltage may correspond to $V_{WL-HIGH}$, which may be larger in magnitude than V_{WL-LOW} , e.g., approximately 500 mV, or it may be less than V_{WL-LOW} . In some embodiments, the difference between V_{WL-LOW} and $V_{WL-HIGH}$ may be generally constant and predetermined, or it may vary and be determined at runtime. Similarly, the values of V_{WL-LOW} and $V_{WL-HIGH}$ may be generally constant and predetermined, or they may vary and be determined at runtime.

Before beginning to sense the second value, the controller 152 may reset the counter 90 and signal the interfuser 124 that the second value is being sensed, e.g., by signaling the inter-

17

fuser 124 to latch the second value. In some embodiments, the counter 90 may output the first value and the second value after both are sensed. The controller 152 may delay between ending the first sensing time and initiating the second sensing time to allow the quantizing circuit 148 to reach steady-state operation, or the controller 152 may begin the second sensing time concurrent to the first sensing time.

In the embodiment illustrated by FIG. 21, if the voltage of the floating gate corresponds to trace 162, the first value may correspond to a bit-line current of I_1 , and the second value may correspond to a bit-line current of I_2 . Thus, in this embodiment, I_2 is greater than I_1 , but in other embodiments, e.g., embodiments with other types of data locations, the traces may have a different shape.

Next, in the process of 156 (FIG. 22), the first value may be combined with the second value to identify data conveyed by the data location, as illustrated by block of 164. Combining the first value with the second value may include receiving the first value and the second value in the interfuser 124 from the counter 90 and signaling the interfuser 124 to combine the first value with the second value via the state signal path 130. As with several of the previously described embodiments, the interfuser 124 may combine the values with a variety of mathematical operations, including addition, subtraction, multiplication, and division. For example, the interfuser 124 may calculate a sum of the first value and the second value or a difference between the first value and the second value. In some embodiments, the interfuser 124 may calculate a slope using the first value, the second value, and the difference between V_{WL-LOW} and $V_{WL-HIGH}$. In a specific example, the first value and second value may be combined using Equation 4 described above by letting C_1 equal of the first value and C_2 equal a second value.

In other embodiments, additional values may be sensed at different gate voltages. For example, a third value may be sensed by sensing the floating-gate transistor 150 at a third gate voltage, which may be different from both the first gate voltage and the second gate voltage. Combining the first value, the second value, and the third value may, in some embodiments, include calculating a second-order derivative.

The process 156 may be used both when reading from and when writing to the floating-gate transistor 150. When writing to the floating-gate transistor 150, in some embodiments, the charge on the floating gate may be incrementally adjusted until the charge corresponds to the data being written to the floating-gate transistor 150. Between each adjustment of the charge, the floating-gate transistor 150 may be read with the process 156 to determine whether the floating-gate transistor 150 stores the correct value. If the floating-gate transistor 150 stores the correct value, the writing process may stop. Otherwise, the charge may be adjusted by another increment.

FIG. 23 illustrates another example of a quantizing circuit 166, which as described below, may be configured to vary two or more different parameters. In this embodiment, a controller 168 connects to both the inverting input of the comparator 96 via the reference voltage signal path 126 and the gate of the floating-gate transistor 150 via the word line 154. The controller 168 may be configured to vary both the gate voltage of the floating-gate transistor 150 V_{GS} and the reference voltage V_{REF} , either at substantially the same time, in sequence, or both.

The quantizing circuit 166, in certain embodiments, may execute a reading process 170 illustrated by FIG. 24. The illustrated process 170 begins with sensing a first value by sensing a data location (e.g., the floating-gate transistor 150) at a first gate voltage and a first reference voltage, as illustrated by block 172. This act may also include resetting or

18

presetting the counter 90 via the reset signal path 128 before sensing the first value. The first value may correspond to a count generated by the counter 90 during a first sensing time, and this count may be transferred to the interfuser 124 (e.g., latched) at the end of the first sensing time. After the count is transferred, the counter 128 may be reset, and the controller 168 may pause while the quantizing circuit 166 reaches steady state. In some embodiments, the controller 168 may identify the first value to the interfuser 124 via the state signal path 130.

Next in the process 170 (FIG. 24), a second value may be sensed by sensing the data location at a second gate voltage and the first reference voltage, as illustrated by block 174. As with the previous act, this act may include resetting the counter before sensing the second value and identifying the second value to the interfuser 124. The second gate voltage may be different from the first gate voltage, for example, more than 500 mV larger.

After sensing the second value, a third value may be sensed by sensing the data location at the first gate voltage and a second reference voltage, as illustrated by block 176. The second reference voltage may be different from the first reference voltage used in the preceding to acts illustrated by the blocks 172 and 174, e.g., more than 500 mV larger. This act may include resetting the counter 90 before determining the third value during a third sensing time and identifying the third value to the interfuser 124. The interfuser 124 may store the first value and the second value in memory while waiting for the third value, and in some embodiments, the interfuser 124 may store all three values in memory at generally the same time.

In some embodiments, the third value may be sensed when the data location is at the second gate voltage and the second reference voltage rather than when the data location is that the first gate voltage and the second reference voltage. In other embodiments, a fourth value may be sensed under these conditions. Other embodiments include sensing the data location with each permutation of three different gate voltages and three different reference voltages to gather nine values.

Next in the process 170 (FIG. 24), the first value may be combined with the second and third values to identify data conveyed by the data location, as illustrated by block 178. In some embodiments, to initiate this act, the controller 168 may signal the interfuser 124 via the state signal path 130 to combine these values and output them on the input/output bus 92. As with many of the other embodiments, combining may take a variety of forms, including those described above. By way of example, the values may be combined with the following equation (Equation 5), in which C_1 , C_2 , and C_3 corresponds to the first, second, and third values respectively and E_1 , E_2 , and E_3 are empirically or analytically determined constants:

$$\text{Data} = E_1 \cdot C_1 + E_2 \cdot C_2 + E_3 \cdot C_3$$

Thus the process 170 may read data by sensing a plurality of values under different conditions and combining the values to identify stored data. Sensing the values under differing conditions may tend to increase the resolution of the quantizing circuit 166 because the values may correspond to a profile of the data location rather than just a response of the data location to a single stimulus. Thus, much like knowing a persons height and weight is more useful for identifying a person than having two measurements of their height, the plurality of values sensed by the quantizing circuit may tend to aid in identifying data stored by the data locations.

FIG. 25 depicts an exemplary processor-based system 310 that includes the memory device 12 (FIG. 2). Alternatively or

additionally, the system **310** may include the imaging device **13**. The system **310** may be any of a variety of types such as a computer, pager, cellular phone, personal organizer, control circuit, etc. In a typical processor-based system, one or more processors **312**, such as a microprocessor, control the processing of system functions and requests in the system **310**. The processor **312** and other subcomponents of the system **310** may include quantizing circuits, such as those discussed above.

The system **310** typically includes a power supply **314**. For instance, if the system **310** is a portable system, the power supply **314** may advantageously include a fuel cell, permanent batteries, replaceable batteries, and/or rechargeable batteries. The power supply **314** may also include an AC adapter, so the system **310** may be plugged into a wall outlet, for instance. The power supply **314** may also include a DC adapter such that the system **310** may be plugged into a vehicle cigarette lighter, for instance.

Various other devices may be coupled to the processor **312** depending on the functions that the system **310** performs. For instance, a user interface **316** may be coupled to the processor **312**. The user interface **316** may include buttons, switches, a keyboard, a light pen, a mouse, a digitizer and stylus, and/or a voice recognition system, for instance. A display **318** may also be coupled to the processor **312**. The display **318** may include an LCD, an SED display, a CRT display, a DLP display, a plasma display, an OLED display, LEDs, and/or an audio display, for example. Furthermore, an RF sub-system/baseband processor **320** may also be coupled to the processor **312**. The RF sub-system/baseband processor **320** may include an antenna that is coupled to an RF receiver and to an RF transmitter (not shown). One or more communication ports **322** may also be coupled to the processor **312**. The communication port **322** may be adapted to be coupled to one or more peripheral devices **324** such as a modem, a printer, a computer, or to a network, such as a local area network, remote area network, intranet, or the Internet, for instance.

The processor **312** generally controls the system **310** by implementing software programs stored in the memory. The memory is operably coupled to the processor **312** to store and facilitate execution of various programs. For instance, the processor **312** may be coupled to the volatile memory **326** which may include Dynamic Random Access Memory (DRAM) and/or Static Random Access Memory (SRAM). The volatile memory **326** is typically large so that it can store dynamically loaded applications and data. As described further below, the volatile memory **326** may be configured in accordance with embodiments of the present invention.

The processor **312** may also be coupled to the memory device **12**. The memory device **12** may include a read-only memory (ROM), such as an EPROM, and/or flash memory to be used in conjunction with the volatile memory **326**. The size of the ROM is typically selected to be just large enough to store any necessary operating system, application programs, and fixed data. Additionally, the non-volatile memory **328** may include a high capacity memory such as a tape or disk drive memory.

The memory device **10** and volatile memory **326** may store various types of software, such as an operating system or office productivity suite including a word processing application, a spreadsheet application, an email application, and/or a database application.

While the invention may be susceptible to various modifications and alternative forms, specific embodiments have been shown by way of example in the drawings and have been described in detail herein. However, it should be understood that the invention is not intended to be limited to the particular

forms disclosed. Rather, the invention is to cover all modifications, equivalents, and alternatives falling within the spirit and scope of the invention as defined by the following appended claims.

What is claimed is:

1. A method, comprising:

generating a first value by sensing a data location under a first condition, wherein the first condition comprises a first voltage or a first current applied to the data location; generating a second value by sensing the data location under a second condition, wherein the second condition comprises a second voltage or a second current applied to the data location; and combining the first value with the second value to identify data conveyed by the data location.

2. The method of claim 1, wherein generating the first value comprises generating a count at a counter while a reference voltage is at one level, latching the count, and resetting the counter.

3. The method of claim 2, wherein generating the second value comprises generating a second count while a reference voltage is at a second level and latching the second count.

4. The method of claim 3, wherein combining the first value with the second value comprises using a fusion algorithm configured to generate a single output value based on the first value and the second value.

5. The method of claim 1, wherein sensing a data location under a first condition comprises quantizing and filtering a value read from the data location.

6. A method, comprising:

generating a first value by sensing a data location under a first condition; generating a second value by sensing the data location under a second condition; generating a third value by sensing the data location under a third condition that is different from the first condition and the second condition; and combining the first value with the second value to identify data conveyed by the data location.

7. The method of claim 6, comprising combining the third value with the first value and the second value.

8. The method of claim 1, wherein generating the first value comprises sensing a voltage or a current with a delta-sigma modulator.

9. A system, comprising:

a data location; a controller coupled to the data location, wherein the controller is configured to vary a parameter of the data location to generate a first analog output and a second analog output; and a delta-sigma modulator coupled to the data location and configured to generate a first digital output based on the first analog output and a second digital output based on the second analog output.

10. The system of claim 9, comprising a digital filter coupled to the delta-sigma modulator and configured to:

sense a first value of the data location based on the first digital output; and sense a second value of the data location based on the second digital output.

11. The system of claim 10, comprising an interfuser coupled to the digital filter and configured to combine the first value and the second value to identify data conveyed by the data location.

21

12. The system of claim 11, wherein the interfuser is configured to combine the first value with the second value by adding, subtracting, dividing, multiplying, or a combination thereof.

13. The system of claim 11, wherein the interfuser is configured to combine the first value with the second value by using a data-fusion algorithm. 5

14. The system of claim 11, wherein the controller is configured to vary a reference voltage supplied to the delta-sigma modulator to generate a third digital output from the delta-sigma modulator. 10

15. The system of claim 14, wherein the digital filter is configured to sense a third value of the data location based on the first third output, wherein the interfuser is configured to combine the first value with the second and third values to identify data conveyed by the data location. 15

16. A system, comprising:

a delta-sigma modulator configured to:

- receive a first indication of a data location operating under a first condition;
- generate a first digital output based on the received first indication;
- receive a second indication of the data location operating under a second condition; and

22

generate a second digital output based on the received second indication;

a digital filter configured to:

- generate a first value based on the first indication; and
- generate a second value based on the second indication;

and

an interfuser configured to combine the first value with the second value to identify data conveyed by the data location.

17. The system of claim 16, comprising a controller configured to vary a parameter of the data location to generate the first and second indications.

18. The system of claim 17, comprising the data location, wherein the data location comprises a floating gate transistor.

19. The system of claim 17, wherein the controller is configured to vary a parameter of the delta-sigma modulator.

20. The system of claim 16, wherein the delta-sigma modulator is configured to receive a third indication of a data location operating under a third condition and generate a third digital output based on the received third indication, wherein the digital filter is configured to generate a third value based on the third indication.

* * * * *